



2013-2014 INFINITE EDGE TIMING AND POST SETTINGS CHART

A Settings					B Settings					C Settings				
Module	Draw Weight	Draw Length	Draw Weight	Draw Length	Module	Draw Weight	Draw Length	Draw Weight	Draw Length	Module	Draw Weight	Draw Length	Draw Weight	Draw Length
Number	(Max. setting*)	(Max. setting*)	(Min. setting**)	(Min. setting**)	Number	(Max. setting*)	(Max. setting*)	(Min. setting**)	(Min. setting**)	Number	(Max. setting*)	(Max. setting*)	(Min. setting**)	(Min. setting**)
1	70.0	30	24.4	29 7/8	1	64.1	29 1/4	24.1	29	1	60.7	28 9/16	23.3	28 1/2
1.5	70.0	29 9/16	23.4	29 3/8	1.5	63.7	28 3/4	23.0	28 3/4	1.5	60.2	28 1/16	22.4	28
2	70.0	29 1/16	22.5	28 15/16	2	62.8	28 3/16	20.9	28 1/16	2	59.1	27 1/2	20.9	27 1/2
2.5	70.0	28 5/8	21.6	28 7/16	2.5	62.3	27 11/16	20.1	27 5/8	2.5	58.3	27 1/16	19.8	26 7/8
3	70.0	28 11/16	20.7	27 5/8	3	61.7	27 1/8	19.3	27	3	57.5	26 1/2	19.0	26 3/8
3.5	70.0	27 9/16	20.1	27 3/8	3.5	61.4	26 11/16	18.6	26 1/2	3.5	56.6	26	18.2	25 15/16
4	70.0	27 1/8	19.8	26 7/8	4	61.1	26 1/8	18.7	26	4	55.5	25 1/2	17.8	25 1/4
4.5	70.0	26 9/16	19.2	26 7/16	4.5	60.7	25 5/8	18.1	25 1/2	4.5	54.6	25	17.1	24 7/8
5	69.4	26 1/16	18.5	25 7/8	5	60.2	25	17.4	24 7/8	5	53.8	24 1/2	16.3	24 5/16
5.5	69.0	25 5/8	17.8	25 3/8	5.5	59.4	24 9/16	16.7	24 1/2	5.5	52.7	23 7/8	15.5	23 3/4
6	68.9	25 1/16	17.2	24 7/8	6	59.0	24	15.9	23 7/8	6	51.5	23 7/16	14.8	23 1/4
6.5	67.9	24 5/8	16.5	24 1/8	6.5	58.5	23 9/16	15.1	23 3/8	6.5	50.8	22 7/8	14.0	22 5/8
7	67.5	24	15.9	23 3/4	7	57.6	22 15/16	14.5	22 7/8	7	49.9	22 1/4	13.3	22 1/8
7.5	66.8	23 1/2	15.4	23 1/4	7.5	56.6	22 3/8	13.9	22 1/4	7.5	48.5	21 5/8	12.6	21 1/2
8	66.0	23	14.9	22 5/8	8	56.2	21 7/8	13.3	21 3/4	8	47.3	21 1/16	11.8	20 7/8
8.5	64.9	22 1/2	14.4	22	8.5	54.3	21 3/8	12.7	21	8.5	45.6	20 1/2	11.2	20 1/2
9	63.6	21 15/16	13.8	21 3/4	9	52.9	20 3/4	12.0	20 1/2	9	43.9	20	10.6	19 3/4
9.5	62.7	21 1/2	13.2	21 1/8	9.5	51.2	20 1/4	11.4	20 1/8	9.5	41.9	19 3/8	9.9	19 1/8
10	61.3	20 15/16	13.2	20 1/2	10	49.3	19 3/4	10.7	19 1/2	10	39.6	18 5/8	9.1	18 1/2
10 1/2	59.3	20 7/16	12.5	19 7/8	10.5	47.3	19	10.0	18 3/4	10.5	37.5	18 1/4	8.4	17 3/4
11	58.0	19 3/4	11.8	19 1/2	11	45.2	18 1/2	9.3	18 1/4	11	35.4	17 1/2	7.8	17 1/4
11.5	58.0	19 3/8	11.2	19	11.5	43.2	18	8.7	17 3/4	11.5	32.9	17	7.1	16 3/4
12	58.0	18 15/16	10.7	18 1/2	12	41.6	17 1/2	8.1	17 1/4	12	30.6	16 3/8	6.5	16 1/4
12.5	58.0	18 3/8	10.3	17 7/8	12.5	41.6	17	7.8	16 1/2	12.5	28.1	15 3/4	5.9	15 1/2
13	58.0	17 13/16	10.3	17 1/2	13	41.6	16 1/2	7.7	16 1/4	13	27.5	15	5.4	14 3/4
13.5	58.0	17 3/8	10.3	17	13.5	41.6	15 7/8	7.7	15 1/2	13.5	27.5	14 5/8	5.4	14 1/4
14	58.0	17 1/8	10.3	16 1/2	14	41.6	15 3/8	7.7	15	14	27.5	14 1/8	5.4	13 3/4
14.5	58.0	16 3/4	10.3	16 1/4	14.5	41.6	15	7.7	14 3/4	14.5	27.5	13 5/8	5.4	13 1/4

NOTE: Bold boxed settings above are manufacturer recommendations for adjustment characteristics of bow. "A" settings achieve best performance and let-off properties, while "B" and "C" settings achieve the lowest draw weight and draw length conditions. **String stop provided with bow is functional for "A" settings and should be removed for "B" and "C" settings.**

*Max. setting refers to the limb bolts being tightened all the way in.

**Min. setting refers to the limb bolts being turned all the way out.



2011-2014 TIMING, MOD, AND POST SETTINGS CHART

2014 MODEL	TIMING MARK	LETOFF	MOD LETTER	MOD 1 Draw* Set	1.5 Draw* Set	2 Draw* Set	2.5 Draw* Set	3 Draw* Set	3.5 Draw* Set	4 Draw* Set	4.5 Draw* Set	5 Draw* Set	5.5 Draw* Set	6 Draw* Set	6.5 Draw* Set	7 Draw* Set	7.5 Draw* Set	8 Draw* Set	
CARBON CURE	Cable centered between marks on cam	80%	CDO	30.5 • 1	30 • 1.5	29.5 • 2	29 • 2.5	28.5 • 3	28 • 3.5	27.5 • 4	27 • 4.5								
INFINITE EDGE	Reference previous page or owners manual																		
CORE	Cable centered between marks on cam	80%	DX	30 • 1	29.5 • 1.5	29 • 2	28.5 • 2.5	28 • 3	27.5 • 3.5	27 • 4	26.5 • 4.5	26 • 5	25.5 • 5.5	25 • 6					
ATOMIC - A SETTING	Cable centered between marks on cam	70%	ATC	24 • 1	23.5 • 1.5	23 • 2	22.5 • 2.5	22 • 3	21.5 • 3.5	21 • 4	20.5 • 4.5	20 • 5	19.5 • 5.5	19 • 6	18.5 • 6.5	18 • 7	17.5 • 7.5	17 • 8**	
ATOMIC - B SETTING	Cable centered between marks on cam	70%	ATC	23.5 • 1	23 • 1.5	22.5 • 2	22 • 2.5	21.5 • 3	21 • 3.5	20.5 • 4	20 • 4.5	19.5 • 5	18.5 • 5.5	18 • 6	17.5 • 6.5	17 • 7	16.5 • 7.5	16 • 8***	
2013 MODEL	TIMING MARK	LETOFF	MOD LETTER	MOD 1 Draw* Set	1.5 Draw* Set	2 Draw* Set	2.5 Draw* Set	3 Draw* Set	3.5 Draw* Set	4 Draw* Set	4.5 Draw* Set	5 Draw* Set	5.5 Draw* Set	6 Draw* Set	6.5 Draw* Set	7 Draw* Set	7.5 Draw* Set	8 Draw* Set	
OUTLAW	Cable centered between marks on cam	80%	DT	30.5 • 1	30 • 1.5	29.5 • 2	29 • 2.5	28.5 • 3	28 • 3.5	27.5 • 4	27 • 4.5	26.5 • 5							
INFINITE EDGE	Reference previous page or owners manual																		
CORE	Cable centered between marks on cam	80%	DX	30 • 1	29.5 • 1.5	29 • 2	28.5 • 2.5	28 • 3	27.5 • 3.5	27 • 4	26.5 • 4.5	26 • 5	25.5 • 5.5	25 • 6					
ATOMIC - A SETTING	Cable centered between marks on cam	70%	ATC	24 • 1	23.5 • 1.5	23 • 2	22.5 • 2.5	22 • 3	21.5 • 3.5	21 • 4	20.5 • 4.5	20 • 5	19.5 • 5.5	19 • 6	18.5 • 6.5	18 • 7	17.5 • 7.5	17 • 8**	
ATOMIC - B SETTING	Cable centered between marks on cam	70%	ATC	23.5 • 1	23 • 1.5	22.5 • 2	22 • 2.5	21.5 • 3	21 • 3.5	20.5 • 4	20 • 4.5	19.5 • 5	18.5 • 5.5	18 • 6	17.5 • 6.5	17 • 7	16.5 • 7.5	16 • 8***	
2012 MODEL	TIMING MARK	LETOFF	MOD LETTER	MOD 1 Draw* Set	1.5 Draw* Set	2 Draw* Set	2.5 Draw* Set	3 Draw* Set	3.5 Draw* Set	4 Draw* Set	4.5 Draw* Set	5 Draw* Set	5.5 Draw* Set	6 Draw* Set	6.5 Draw* Set	7 Draw* Set	7.5 Draw* Set	8 Draw* Set	
DEAD EYE	Cable centered between marks on cam	80%	DT	30 • 1	29.5 • 1.5	29 • 2	28.5 • 2.5	28 • 3	27.5 • 3.5	27 • 4	26.5 • 4.5	26 • 5							
FUGITIVE	Cable centered between marks on cam	80%	DT	30 • 1	29.5 • 1.5	29 • 2	28.5 • 2.5	28 • 3	27.5 • 3.5	27 • 4	26.5 • 4.5	26 • 5							
OUTLAW	Cable centered between marks on cam	80%	DT	30.5 • 1	30 • 1.5	29.5 • 2	29 • 2.5	28.5 • 3	28 • 3.5	27.5 • 4	27 • 4.5	26.5 • 5							
RAZOR EDGE	Cable centered between marks on cam	75%	DY	N/A*															
ATOMIC - A SETTING	Cable centered between marks on cam	70%	ATC	24 • 1	23.5 • 1.5	23 • 2	22.5 • 2.5	22 • 3	21.5 • 3.5	21 • 4	20.5 • 4.5	20 • 5	19.5 • 5.5	19 • 6	18.5 • 6.5	18 • 7	17.5 • 7.5	17 • 8**	
ATOMIC - B SETTING	Cable centered between marks on cam	70%	ATC	23.5 • 1	23 • 1.5	22.5 • 2	22 • 2.5	21.5 • 3	21 • 3.5	20.5 • 4	20 • 4.5	19.5 • 5	18.5 • 5.5	18 • 6	17.5 • 6.5	17 • 7	16.5 • 7.5	16 • 8***	
2011 MODEL	TIMING MARK	LETOFF	MOD LETTER	MOD 1 Draw* Set	1.5 Draw* Set	2 Draw* Set	2.5 Draw* Set	3 Draw* Set	3.5 Draw* Set	4 Draw* Set	4.5 Draw* Set	5 Draw* Set	5.5 Draw* Set	6 Draw* Set	6.5 Draw* Set	7 Draw* Set	7.5 Draw* Set	8 Draw* Set	
DEAD EYE	Cable centered between marks on cam	80%	DT	30 • 1	29.5 • 1.5	29 • 2	28.5 • 2.5	28 • 3	27.5 • 3.5	27 • 4	26.5 • 4.5	26 • 5							
FUGITIVE	Cable centered between marks on cam	80%	DT	30 • 1	29.5 • 1.5	29 • 2	28.5 • 2.5	28 • 3	27.5 • 3.5	27 • 4	26.5 • 4.5	26 • 5							
OUTLAW	Cable centered between marks on cam	80%	DT	30.5 • 1	30 • 1.5	29.5 • 2	29 • 2.5	28.5 • 3	28 • 3.5	27.5 • 4	27 • 4.5	26.5 • 5							
RAZOR EDGE	Power cable between marks on cam	75%	DY	N/A*															
NUCLEAR ICE	N/A	70%	NI	N/A*															

*Mod number is equal to draw length. For example, mod number 22 equals a 22" draw length. There are no posts to set on this bow.

**Mod settings and draw lengths continue in 1/2 step increments to 14 • 11 (Mod number 11, draw length 14")

***Mod settings and draw lengths continue in 1/2 step increments to 12 • 11 (Mod number 11, draw length 12")



2008-2010 TIMING, MOD, AND POST SETTINGS CHART

2010 MODEL	TIMING MARK	LETOFF	MOD LETTER	MOD 1 Draw*Set	1.5 Draw*Set	2 Draw*Set	2.5 Draw*Set	3 Draw*Set	3.5 Draw*Set	4 Draw*Set	4.5 Draw*Set	5 Draw*Set	5.5 Draw*Set	6 Draw*Set	6.5 Draw*Set	7 Draw*Set	7.5 Draw*Set	8 Draw*Set
ICEMAN FLX	Centered between dots 5 and 7	65-80%	ICE	30 • 9.25	29.5 • 8.9	29 • 7.8	28.5 • 6.8	28 • 6	27.5 • 5.2	27 • 4.8	26.5 • 3.9	26 • 3.4	25.5 • 2.9	25 • 2.3	24.5 • 1.8	24 • 1.2		
BLACK ICE FLX	7 and 10 dots centered equilateral about dots	65-80%	DP	30 • 1	29.5 • 1.5	29 • 2	28.5 • 2.5	28 • 3	27.5 • 3.5	27 • 4	26.5 • 4.5	26 • 5	25.5 • 5.5	25 • 6				
DIAMOND STUD	7 dots	65-80%	STUDR	30 • 9.5	29.5 • 8.9	29 • 8.2	28.5 • 7.6	28 • 7.2	27.5 • 6.4	27 • 5.8	26.5 • 5.0	26 • 4.2	25.5 • 3.1	25 • 2.1				
ROCK 2	Centered between dots 5 and 7	65-80%	DM	30 • 1	29.5 • 1.5	29 • 2	28.5 • 2.5	28 • 3	27.5 • 3.5	27 • 4	26.5 • 4.5	26 • 5	25.5 • 5.5	25 • 6	24.5 • 6.5	24 • 7		
RAZOR EDGE	Power cable between marks on cam	75%	DY	N/A*														
NUCLEAR ICE	N/A	70%	NI	N/A*														
2009 MODEL	TIMING MARK	LETOFF	MOD LETTER	MOD 1 Draw*Set	1.5 Draw*Set	2 Draw*Set	2.5 Draw*Set	3 Draw*Set	3.5 Draw*Set	4 Draw*Set	4.5 Draw*Set	5 Draw*Set	5.5 Draw*Set	6 Draw*Set	6.5 Draw*Set	7 Draw*Set	7.5 Draw*Set	8 Draw*Set
ICEMAN	Centered between dots 5 and 7	65-80%	ICE	30 • 9.7	29.5 • 8.8	29 • 8.0	28.5 • 7.2	28 • 6.4	27.5 • 4.9	27 • 4.5	26.5 • 3.9	26 • 3.4	25.5 • 2.8	25 • 2.3	24.5 • 1.7	24 • 1.2		
BLACK ICE	2 dots ISF	65-80%	DP	30 • 8.9	29.5 • 8.3	29 • 7.7	28.5 • 6.8	28 • 6.0	27.5 • 5.1	27 • 4.2	26.5 • 3.2	26 • 2.2						
DIAMOND STUD	7 dots	65-80%	STUDR	30 • 9.5	29.5 • 8.9	29 • 8.2	28.5 • 7.6	28 • 7.2	27.5 • 6.4	27 • 5.8	26.5 • 5.0	26 • 4.2	25.5 • 3.1	25 • 2.1				
ROCK	1 dot OSF	65-80%	DM	30 • 8.2	29.5 • 7.7	29 • 7.2	28.5 • 7	28 • 6.8	27.5 • 6.5	27 • 6.2	26.5 • 5.8	26 • 5.5	25.5 • 5.2	25 • 4.8	24.5 • 4.6	24 • 4.5	23.5 • 3.8	23 • 3.6
RAZOR EDGE	Power cable between marks on cam	75%	DY	N/A*														
MARQUIS	1 dot ISF	65-75%	DUP	30 • 9.3	29.5 • 8.6	29 • 8.0	28.5 • 7.4	28 • 6.9	27.5 • 6.3	27 • 5.5	26.5 • 4.8	26 • 4.1						
NUCLEAR ICE	N/A	70%	NI	N/A*														
2008 MODEL	TIMING MARK	LETOFF	MOD LETTER	MOD 1 Draw*Set	1.5 Draw*Set	2 Draw*Set	2.5 Draw*Set	3 Draw*Set	3.5 Draw*Set	4 Draw*Set	4.5 Draw*Set	5 Draw*Set	5.5 Draw*Set	6 Draw*Set	6.5 Draw*Set	7 Draw*Set	7.5 Draw*Set	8 Draw*Set
MARQUIS	1 single dot .240 ISF	80%	DUP	30 • 9.3	29.5 • 8.6	29 • 8	28.5 • 7.4	28 • 6.9	27.5 • 6.3	27 • 5.5	26.5 • 4.8	26 • 4.1						
BLACK ICE	2 dots on inside of limb	80%	DP	30 • 8.2	29.5 • 7.6	29 • 7	28.5 • 6.3	28 • 5.7	27.5 • 4.8	27 • 4	26.5 • 3.1	26 • 2.3						
LIBERTY	4 3/4 Dots ISF	80%	DB	30 • 7.9	29.5 • 7	29 • 6.2	28.5 • 5.3	28 • 4.5	27.5 • 3.7	27 • 3	26.5 • 2.2	26 • 1.5	25.5 • .7	25 • 0				
JUSTICE	1.5 Dots inside of limb	80%	DB	31 • End	30.5 • 9.3	30 • 8.8	29.5 • 8.3	29 • 7.8	28.5 • 7.3	28 • 6.8	27.5 • 6.3	27 • 5.8	26.5 • 5.1	26 • 4.5				
ROCK	1 dot OSF	80%	DM	30 • 8.2	29.5 • 7.7	29 • 7.2	28.5 • 7	28 • 6.8	27.5 • 6.5	27 • 6.2	26.5 • 5.8	26 • 5.5		25 • 4.8		24 • 4.5		23 • 3.6
EDGE/CUTTER	Cutting last web in half ISF	75%	DK	N/A*														

*Mod number is equal to draw length. For example, mod number 22 equals a 22" draw length. There are no posts to set on this bow.

